



ONE-LINE DIAGRAM

ITEM NO.	DESCRIPTION	FURNISHED BY		INSTALLED BY	
		O.G. & E.	CONSUMER	O.G. & E.	CONSUMER
1	Service Lateral Raceway		X		X
2	Load-Break Disconnect	See Note 1	X		X
3	Meter Base	X			X
4	Self-Contained Meter	X		X	
5	Service Lateral	X		X	
6	Service Raceway		X		X
* 7	Service Equipment		X		X
* 8	Grounding Electrode & Grounding Electrode Conductor		X		X

* Not Shown

Notes:

1. OG&E to furnish Load-Break Disconnect for 480-volt service in Arkansas
2. OG&E to secure load-break disconnect box with series 1 lock (stk#301236).
3. OG&E equipment is to be installed on outside surface of structure and is not to be recessed.
4. Refer to U16 for proper identification and marking.
5. Refer to U760 and U760.1
6. OG&E equipment not to be used for customer grounding.

**METER INSTALLATION
FOR SELF-CONTAINED METER
480 OR 480Y/277-VOLTS 200-AMPERES MAXIMUM**

The following is a suggested configuration for meter bases for overhead and underground meters in residential and commercial applications. OGE Energy Corp., its subsidiaries and affiliates, disclaim any and all liability for the construction or maintenance practices relating to such suggested configuration. Each individual, company, or entity engaging the work associated with this configuration bears full responsibility for its, his, or her own occupational training, and compliance with all applicable local, state, and national laws and regulations. The configuration is not intended to replace the training, know-how, or instruction that may be needed for safe construction or maintenance.

APPROVED Signatures on File

SUPERSEDES JUL 2019 ISSUE