



Notes:

- 1 Total length of pole is to be a minimum of 18 feet and diameter of pole at ground line is to be a minimum of 7-inches.
- 2 Disconnect cabinet to be locked by OG&E.
- 3 OG&E to secure Energized Parts and Switch Position with Series 1 lock (301236).

NOTES:

- A. 12-ft over areas restricted to pedestrians or other traffic less than 8-ft in height.
16-ft over areas subject to any traffic greater than 8ft. in height.
For swimming pools see D262.4 or D262.6.
For other situations see D262, D262.1, D262.4 or D262.5.
- B. Use 1/2" thru bolts on top and bottom to mount meter base.

Item no.	DESCRIPTION	Furnished by		Installed by	
		O.G.E.	Consumer	O.G.E.	Consumer
1	Service head		X		X
± 2	Service pole See note A		X		X
3	200 Amp Fused Disconnect		X		X
4	Meter base	X			X
5	Service entrance conductor		X		X
6	Service raceway		X		X
7	Service drop bracket	X			X
8	Service drop	X		X	
9	Meter	X		X	
10	Grounding electrode Conductor		X		X
11	Grounding electrode		X		X
12	Disconnect Switch		X		X
13	1/2" Mounting bolts See note B		X		X

‡ Pressure treated southern yellow pine

**ALTERNATE
480V CONSUMER SERVICE POLE
REFER TO U773.8 FOR PRIMARY CHOICE**

The following is a suggested configuration for meter bases for overhead and underground meters in residential and commercial applications. OGE Energy Corp., its subsidiaries and affiliates, disclaim any and all liability for the construction or maintenance practices relating to such suggested configuration. Each individual, company, or entity engaging the work associated with this configuration bears full responsibility for its, his, or her own occupational training, and compliance with all applicable local, state, and national laws and regulations. The configuration is not intended to replace the trainin know-how or instruction that ma be needed for safe construction or maintenance.
 APPROVED Signatures on File
 SUPERSEDES JUL 2018 ISSUE